


for HVAC, Compressors, and Special Uses



*CNX-209-120
Special Purpose contactor*

Special Needs Require Special Contactors

CNX Special Purpose Contactors are rated by FLA & LRA as well as resistive current rated - primarily to meet the demands of the HVAC and compressor markets. A member of the CA7 line of contactors, CNX contactors have all the flexibility of a CA7 contactor, like easy coil change out, DIN rail mounting and field installable auxiliaries, as well as mechanical interlocks not normally associated with true definite purpose contactors. CNX contactors may also be combined with CEP7 overload relays to make a special purpose starter. CNX contactors are cUL rated and labeled as well as ARI (Air Conditioning and Refrigeration Institute) approved.




A KWIKstarter for up to 30 HP

Sprecher + Schuh's "build-from-stock" starter is housed in a high impact, non-metallic, cUL Approved, Type 1/12/4/4X enclosure. Built for convenience, space savings and economy, the CNX KWIKstarter is efficiently designed to use a CNX Contactor and appropriately selected overload - either the CEP7 solid state version overload (Q1 dimension).

Sized for most industrial applications

CNX KWIKstarters will control motors up to 30HP @ 460V 3-phase and 7 1/2 HP @ 230V Single-Phase in a non-metallic multi-integrity type rated enclosure. This covers specific industrial motor control applications in a very compact package that can be mounted adjacent to or directly on equipment.



Series CNX Non-Reversing, Three Pole Special Purpose Contactors

Full Load Amps	Locked Rotor Amps - 3Ø			Resistive Amps	Maximum Horsepower						Auxiliary Contacts per Contactor		AC Coil (Open type only)
					1 Ø		3 Ø						
	200V 230V	460V	575V		115V	230V	200V/ 208V	230V	460V	575V	NO	NC	Catalog Number
15	91	91	66	25	1-1/2	3	4	5	10	10	1	0	CNX-205-*
											0	1	CNX-206-*
30	180	150	120	40	2	5	7-1/2	10	20	20	1	0	CNX-207-*
											0	1	CNX-208-*
40	240	200	160	50	3	5	10	10	25	25	0	0	CNX-209-00-*
											1	1	CNX-209-10-*
											0	1	CNX-209-01-*
50	300	250	200	65	3	7-1/2	10	15	30	30	0	0	CNX-212-00-*
											1	0	CNX-212-10-*
											0	1	CNX-212-01-*
90	540	450	360	120	~	~	25	30	60	60	0	0	CNX-218-00-*
											1	0	CNX-218-10-*
											0	1	CNX-218-01-*






A.C. Coil Code	Voltage Range	
	50 Hz	60 Hz
024Z	24V	24V
0120	110V	120V
220W	~	208V-240V
0480	440V	480V
0600	550V	600V

* See Coil Code tables

Replace * with coil code.
More voltages available. See catalog.

KWIKstarters with CNX Contactor & CEP7 Overload Relays

	Full Load Amps	Locked Rotor Amps - 3Ø			Resistive Amps	Maximum Horsepower						Auxiliary Contacts per Contactor		cUL Approved - Type 1/12/4/4X IP66 Catalog Number	Dim
		200V 230V	460V	575V		1 Ø		3 Ø				NO	NC		
						115V	230V	200V/ 208V	230V	460V	575V				
KWIKstarter with Start and Raised Stop/Reset															
	30	180	150	120	40	2	5					1	0	CLB-KAX207*-1EEB-3	Q1
								7-1/2	10	20	20	1	0	CL-KAX207*-1EEB-3	Q1
KWIKstarter with Reset only															
	30	180	150	120	40	2	5					1	0	CLB-KAX207*-1EEB-0	Q1
								7-1/2	10	20	20	1	0	CL-KAX207*-1EEB-0	Q1
KWIKstarter with Start-Stop Multi-function or 2-Position Selector Switch															
	40	240	200	160	50	3	5					1	0	CLB-KAX209*-IEFD-P▼	Q2
								10	10	25	25	1	0	CL-UAX209*-IEFD-P▼	Q2
	50	300	250	200	65	3	7-1/2					1	0	CLB-KAX212*-IEFD-P▼	Q2
								10	15	30	30	1	0	CL-KAX212*-IEFD-P▼	Q2

* Replace with Coil Code from table above.

▼ Replace with 3U for Multi-function Start-Stop, 4U for Multi-function I-O, or 6 for Off-On Selector Switch. Pilot light option also available. Contact factory for details.

For more information, or to contact your Sprecher + Schuh representative, visit

www.sprecherschuh.com

Sprecher + Schuh US Division Headquarters • 15910 International Plaza Dr., Houston, TX 77032

Customer Service: (877) 721-5913; Fax: (800) 739-7370