

**Short Circuit Ratings**

	CA9-116	CA9-146	CA9-190	CA9-205	CA9-265	CA9-305	CA9-370	CA9-400	CA9-460	CA9-580	CA9-750	CA9-860	CA9-1060	CA9-1260	CA9-2050	CA9-2650
--	---------	---------	---------	---------	---------	---------	---------	---------	---------	---------	---------	---------	----------	----------	----------	----------

**Short Circuit Coordination (Max. Fuse or Circuit Breaker Rating)**  
per IEC 60947-4-1

100 kA Available Fault Current																	
DIN Fuses -gG																	
Type "2" (400V)	[A]	250	250	315	315	400	500	630	630	630	800	800	1000	1250	~	~	~
80 kA Available Fault Current																	
DIN Fuses -gG																	
Type "2" (690V)	[A]	160	200	315	315	400	425	500	500	630	800	800	1000	1600	~	~	~
70 kA Available Fault Current																	
MCCB																	
Type "2" (400V)	[A]	160	160	320	320	400	630	630	630	630	800	1000	1600	1600	~	~	~

**Short Circuit Coordination (Max. Fuse or Circuit Breaker Rating)**  
per UL 60947 and CSA 22.2 No. 14 (contactor and fuses or circuit breaker only)

10 kA Available Fault Current																	
UL Class RK5 Fuses																	
Type 1 Combination (600V)	[A]	250	250	400	400	~	~	~	~	~	~	~	~	~	~	~	~
82 kA Available Fault Current																	
UL Class J and CSA HRCI-J Fuses																	
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	600	600	1200	1200	~	~	~	~	~
100 kA Available Fault Current																	
UL Class J and CSA HRCI-J Fuses																	
Type 1 Combination (600V)	[A]	250	250	400	400	600	600	800	600	600	~	~	~	~	~	~	~
Type 2 Combination (600V)	[A]	200	200	400	400	600	600	600	600	600	~	~	~	~	~	~	~
18 kA Available Fault Current																	
UL Class L Fuses																	
Type 1 Combination (600V)	[A]	~	~	~	~	800	800	800	~	~	~	~	~	~	~	~	~
30 kA Available Fault Current																	
UL Class L Fuses																	
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	1000	1000	~	~	~	~	~	~	~
85 kA Available Fault Current																	
UL Class L Fuses																	
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	~	~	~	~	1600	1600	~	~	~
100 kA Available Fault Current																	
UL Class L Fuses																	
Type 1 Combination (600V)	[A]	~	~	~	~	~	~	~	800	800	1200	1200	~	~	1600	~	~
Type 2 Combination (600V)	[A]	~	~	~	~	~	~	~	~	~	1200	1200	~	~	~	~	~
42 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (480V)	[A]	~	~	~	~	~	~	~	~	~	1200	1200	~	~	~	~	~
65 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (480V)	[A]	250	250	400	400	800	800	800	800	800	800	800	~	~	~	~	~
84 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (480V)	[A]	~	~	~	~	~	~	~	600	800	~	~	~	~	~	~	~
89 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (480V)	[A]	~	~	~	~	~	~	~	~	~	800	800	~	~	~	~	~
100 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (480V)	[A]	250	250	400	400	800	800	800	~	~	~	~	~	~	~	~	~
25 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 2 Combination (600V)	[A]	250	250	~	~	~	~	~	~	~	~	~	~	~	~	~	~
35 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 2 Combination (600V)	[A]	~	~	400	400	800	800	800	600	800	800	800	~	~	~	~	~
42 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (600V)	[A]	~	~	~	~	800	800	800	600	800	800	800	~	~	~	~	~
50 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (600V)	[A]	250	250	~	~	~	~	~	~	~	800	800	~	~	~	~	~
65 kA Available Fault Current																	
UL Inverse-Time Circuit																	
Type 1 Combination (600V)	[A]	~	~	400	400	400	400	400	~	~	~	~	~	~	~	~	~