Reversing, Three Pole Contactors With DC Coil, Series CAU7 (Open type only)

I_e [A]		Ratings for Switching AC Motors (AC2 / AC3 / AC4)										Auxiliary Contacts per Contactor		Open Type Catalog Number
		kW (50 Hz)				UL/CSA HP (60 Hz)								
						1 Ø		3 Ø						
AC-3	AC-1	230V	400V 415V	500V	690V	115V	230V	200V	230V	460V	575V	NO	NC ❷	
60	100	18.5	32	37	32	**5**	**10**	**15**	**20**	**40**	**50**	0	1	**CAU7-60D-02-✱**
												1 ❸	1	**CAU7-60D-22-✱**
72	100	22	40	45	40	**5**	**15**	**20**	**25**	**50**	**60**	0	1	**CAU7-72D-02-✱**
												1 ❸	1	**CAU7-72D-22-✱**
85	100	25	45	55	45	**7-1/2**	**15**	**25**	**30**	**60**	**60**	0	1	**CAU7-85D-02-✱**
												1 ❸	1	**CAU7-85D-22-✱**
97	130	30	55	55	55	**10**	**20**	**30**	**30**	**75**	**75**	0	1	**CAU7-97D-02-✱**
												1 ❸	1	**CAU7-97D-22-✱**

NOTE: DC and AC coils are not interchangeable. CA7-60D...97D contactors have a two winding, 3-lead coil with built-in late break auxiliary contact and coil suppression. Refer to dimensions starting on page A2:59.



CAU7-85D Reversing (Typical)

Includes:

- DC operating mechanism
- Line side coil terminations
- Mechanical and electrical Interlock ❷
- Reversing power wiring
- Control wiring available; see footnote ❶

Coil Codes ❹❺

DC Coil Code	Voltage
24DD	24V
110DD	110V
220DD	220V

Ordering Instructions

Specify Catalog Number	
Replace (✱) with Coil Code	See Coil Codes on this page.

❶ For control wiring, add suffix **-CW** to catalog number. For example: CAU7-60D-22-✱ becomes CAU7-60D-22-✱**-CW**. Price addition applies.
❷ The NC auxiliary contacts are supplied as part of the mechanical interlock (Cat.# CM7-02) and are used to electrically interlock the contactors.
❸ The NO auxiliary contacts supplied are side mounted. Top mounted NO (or NC) auxiliary contacts must be ordered separately.
❹ Other voltages available, see page A2:29.
❺ Coils for CAU7-60D...97D reversing contactors include an integrated diode surge suppressor.